



ON / OFF

COLOR WHEEL

Can select any color from the color wheel.
Can select Brightness (B) on any selected color.

OPERATIONAL RED LED

Flashes when any remote operation is initiated

**MODE SELECTION
Up & Down**

1. White - Can change Brightness (B) [Default]
2. Color Change - Can change Brightness (B) & Speed (S)
Red, Amber, Green, Aqua, Blue, Purple, White
with initial setting of 2 second delay.
This time can be increased to 4, 6, 8 or 10 Sec
by pressing (S -)
3. Disco - Can change Brightness (B)
4. White Gradual Change - Can change Brightness (B) & Speed (S)
5. Blue Gradual Change - Can change Brightness (B) & Speed (S)
6. Green Gradual Change - Can change Brightness (B) & Speed (S)
7. Red Gradual Change - Can change Brightness (B) & Speed (S)

DEPTH = 20mm

**BRIGHTNESS
Up & Down**

5 Brightness Settings
(100%, 80%, 60%, 40%, 20%)

**SPEED
Up & Down**

5 Speed Settings
(2 sec, 4 sec, 6 sec, 8 sec, 10 sec)

FEATURES

1. Matching Code - Apply power to the receiver. Then press (+) on Speed (S) once within 5 seconds.
The output light will flash white 3 times if matching is successful.
2. Clearing Code - Apply power to the receiver. Hold down (+) on Speed (S) for 3 seconds.
The output light will flash 6 times if clearing the code is successful.
After successfully clearing the existing code a new code will have to be applied
by following the matching code procedure above.
3. 1 Transmitter (PCT-1) can operate an unlimited number of Receivers (PCR-4)
4. 1 Receiver (PCR-4) can be controlled by a maximum of 4 Transmitters (PCT-1)
5. Touching the color wheel will reset any Mode selection.
6. Memory Feature - Remembers color selection after being switched off.
7. Once the transmitter and receiver are successfully coded the receiver will remember the code if powered off.