



ON / OFF (For Channel 5 only)

COLOR WHEEL

Can select any color from the color wheel.
Can select BRIGHTNESS on any selected color.

OPERATIONAL RED LED

Flashes when any remote operation is initiated

MODE SELECTION Up & Down

1. White - Can change BRIGHTNESS [Default]
2. Color Change - Can change BRIGHTNESS & SPEED
Red, Amber, Green, Aqua, Blue, Purple, White with initial setting of 2 second delay.
This time can be increased to 4, 6, 8 or 10 Sec by pressing (SPEED DOWN)
3. Disco - Can change BRIGHTNESS
4. White Gradual Change - Can change BRIGHTNESS & SPEED
5. Blue Gradual Change - Can change BRIGHTNESS & SPEED
6. Green Gradual Change - Can change BRIGHTNESS & SPEED
7. Red Gradual Change - Can change BRIGHTNESS & SPEED

BRIGHTNESS Up & Down

5 Brightness Settings
(100%, 80%, 60%, 40%, 20%)

SPEED Up & Down

5 Speed Settings
(2 sec, 4 sec, 6 sec, 8 sec, 10 sec)

CH1 } On-Off Control
CH2 } for PCR-5
CH3 } 4ch Remote
CH4 } Control System

FEATURES

1. Matching Code - Apply power to the receiver. Then press (SPEED UP) once within 5 seconds.
The output light will flash white 3 times if matching is successful.
2. Clearing Code - Apply power to the receiver. Hold down (SPEED UP) for 3 seconds.
The output light will flash 6 times if clearing the code is successful.
After successfully clearing the existing code a new code will have to be applied by following the matching code procedure above.
3. 1 Transmitter (PCT-5) can operate an unlimited number of Receivers (PCR-4)
4. 1 Receiver (PCR-4) can be controlled by a maximum of 4 Transmitters (PCT-5)
5. Touching the colour wheel will reset any Mode selection.
6. Memory Feature - Remembers color selection after being switched off.
7. Once the transmitter and receiver are successfully coded the receiver will remember the code if powered off.