




When a lighting project calls for a higher level of LED illumination, choose the LM in a 2 LED configuration. To achieve the best effect and utility, install the LM fixture in the wall adjacent to a stairway.

LM: Wall Light

NUMBER OF LEDS:	2
HALOGEN LUMEN OUTPUT EQUIVALENT:	20 Watt
USEFUL LED LIFE (L70):	50,000 hrs avg
INPUT VOLTAGE:	10 to 15V
VA TOTAL: (Use this number to size the transformer)	4.8
WATTS USED:	4.0
LUMENS PER WATT (EFFICACY)	1.6
MAX LUMENS:	6
CCT (Ra)	81.3






LM: Wall Light

FACTORY INSTALLED OPTIONS: Order 1 + 2 (optional) + 3 + 4

Step	Description	Code
1	FIXTURE	LM
2	OPTIONAL ZD	ZD (Refer to the Luxor page in the Lighting Control section)
3	LAMP	2LED (50,000 avg. life hours)
4	FINISH	AB*, AT*, CU, NP*, WG, FW, AL, BZ, DG, WI, VF, SB, FB


EXAMPLE: LM-ZD-2LED-BZ = LM - ZD Option - Two 1LED Boards - Bronze Metallic Finish

PHOTOMETRICS:



Beam angle is calculated using LM-79 method for SSL Luminaires:
 "Beam angle is defined as two times the vertical angle at which the intensity is 50% of the maximum."

MOUNTING FEATURES AND DIMENSIONS:



Perfectly Level Every Time
 The LevelX system allows the composite sleeve to be up to 3/8" out of level, in either direction, while still allowing the faceplate to be laser level.

The secret: The trim attaches to the adjustable reflector assembly - not the composite sleeve or body. Heavy foam gasket keeps light spill to a minimum.

The LM includes two 1LED boards, choice of faceplate finish, 8 ft lead wire and mounting sleeve.

All LM wall lights come standard with amber, green, blue and frosted filters

* May require longer lead time



METALS

-  **AB** = Antique Bronze* (On Copper)
-  **AT** = Antique Tumbled* (On Copper)
-  **CU** = Copper
-  **NP** = Nickel Plate*

POWDER COAT

-  **WG** = White Gloss
-  **FW** = Flat White
-  **AL** = Almond
-  **BZ** = Bronze Metallic
-  **DG** = Desert Granite
-  **WI** = Weathered Iron
-  **VF** = Verde Speckle
-  **SB** = Sedona Brown
-  **FB** = Flat Black